

LED INTELLIGENT LIGHTING CONTROL SYSTEM USER GUIDER

FUNCTION OF REMOTE CONTROLLER:

Product: Remote Controller (Wireless Mobile Controller)

Power: AAA battery×2; **Frequency:** RF-2.4G; **Effective Distance:** 20M (Without Obstacle)

Number of controllable lamps: 1 controller can control 99 groups of lamps, and no limit to the number of lamps in one group.

ID of Lamp: ID of lamp could be 1 to 99.

Multifunctional: ON /OFF, Dimming and Color-temp adjusting,timing ON /OFF, 2 scenes recall,auto dimming,night light.

Copy the ID of Remote Controller: Every remote controller has its ID number.One controller can copy and use the ID number of another controller to control the same lamp, and recover its initial ID number.

Operating method:

Steps of Setup ID number of lamp:

- ①Power on the lamp you want to set by switch.
- ②Press 1 or 2 numbers on the number keys of remote controller, than press “ ID ” key;
- ③Repeat step ② again.
- ④The lamp will turn off automatically.
- ⑤Power off the lamp within 10S then finish setup.If the lamp turn on again automatically,setup is canceled .

Control the lamp:

The function of the keys: as the figure on the right.

Control the single group: press the ID number of the lamp you want to control and then press one functional key(on/off, color temp, brightness).

All-control Model: press “ ALL ” key to control all groups.

TIMING ON/OFF:

Press the ID number of the lamp you want to set, press “ ID ” key.

SET: Press the number key 1-99 , press “ ⌚ ” timing ON key or “ ⌚ ” timing OFF key, then finish setting. Timing units is 10minutes.

Cancel: Press “0” key, then “ ⌚ ” timing ON key or “ ⌚ ” timing OFF key to cancel timing mode.

COPY THE ID OF CONTROLLER:

Press “ S ” key of one controller and “ I ” key of another controller at the same time, keep the distance between the controllers within 10CM for 10S, then finish.

Recovery: Press the “ S ” key and “ ALL ” key of the slave controller for 10S, the controller will recover its ID.

NIGHT LIGHT MODE:

Press the “ * ” key when the lamp is turn off, the lamp is turn on and brightness will be 3% of the rated output.

CIRCLE MODE:

Press “ S ” key twice within 3S while the lamp is ON, the circle mode will begin to show different state of the lamp.

SCENE MODE: Lamp can save two scenes : “A” and “B”

Save:

- ①Adjust the light as your preference.
- ②Press the ID number of the lamp.
- ③Press “ ID ” key and then press “ A ” or “ B ” , the lamp will save the status of lamp.

Recall:

- ①Press the ID number of the lamp.
- ②Press “ A ” or “ B ” .

